

Confidea DI/CI

WIRELESS CHANNEL SELECTOR UNIT

Art. 71.98.0003 / 71.98.0013



Confidea DI




Confidea CI

Description

The Confidea wireless unit combines a slim, contemporary design, excellent intelligibility and ease of use with a robust and reliable wireless connection which sets it apart from traditional wireless systems.

It allows a delegate/chairman of a conference to speak, request-to-speak and listen to the speaker or their preferred available language.

The units are equipped with a microphone On/Off or request-to-speak button and single channel selector including separate OLED display indicating chosen channel number, abbreviated channel name and headphone volume.



The chairman unit comes with an additional priority, next-in-line and system volume adjustment button.

The Confidea DI/CI units have the capability of receiving up to 40 translation channels. Up to 8 microphones can be open at the same time.

Battery management is crucial using a wireless conference system. Therefore Confidea units combine a smart power management with an easy to replace removeable Lithium-ion battery pack. This results in a

controllable and flexible recharging schedule. (Confidea BP, to be ordered separately)

A screw lock connector is provided to connect a removable microphone which is immune against GSM disturbances (MIC 38SL, to be ordered separately).

To prevent eavesdropping and unauthorized access, the Confidea® wireless system and the discussion units have a digital encryption mechanism to keep information of the meeting confidential.

Controls and Features

- Built-in high quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback.
- Microphone On/Off or request-to-speak button with two signalling LEDs
- Two headphone outputs
- One headphone volume adjustment
- One channel Up/Down adjustment
- OLED channel and headphone volume information display
- The chairman version (CI) comes with a priority, next-in-line and system volume adjustment button

Status Control

- Red battery status LED
4 h remaining : 1 Hz blinking
2h remaining : 2 Hz blinking
1h remaining : 4 Hz blinking
- Blue link status LED
Off : connection established
Blinking : low link quality
- Blue link status LED + Microphone LED
Blinking : out of range, shutdown after 2 min.

Connectivity

- Two 3.5 mm jack plugs for headphones
- Battery pack connection
- Screw lock socket to connect removable microphone

Specifications

Technical Data	
Audio quality	16 bit digital
Headphone load impedance	> 32 ohm < 1k ohm
Output power	16.5 mW / 32 ohm
Power Supply	Battery pack
Dimensions	230(w), 130(h), 60(d)
Weight (g)	460
Color	RAL9011
Part number	Confidea DI 71.98.0003 Confidea CI 71.98.0013

Accessories

- Removeable microphone
MIC38SL 71.98.0050
- Battery pack
Confidea BP 71.98.0042
- Transport case
Confidea CHC 71.98.0044
- Headphones
TEL151 71.04.0151